

BH1/BH2 Charger Installation and Mounting Instructions

BH1/BH2 Charger Kit



Figure 1

BH1/BH2 Charger (as pictured) includes:
 Left: Power Supply (as ordered - Figure 3)
 Middle: Charger, Retainer Clip, screw & washer
 Right: 4 screws (for CodeXML Modem)
Note: Battery Handle, Reader, CodeXML Modem and Cable, ordered and sold separately.

Power Supplies - Figure 3



US

Euro/SoAm

UK

Cable Types - Figure 7



USB

RS232

PS2



Wall Mounted
BH1/BH2 Charger



Countertop Mounted
BH1/BH2 Charger

Note Regarding Mounting Screws:

Screws for mounting the assembled BH1/BH2 Charger should not exceed .2" on the shaft or .4" on the head. Screws not included in Assembly Kit.

For further assistance, please contact Code Technical Support: 801 495 2200; or email: support@codecorp.com

BH1/BH2 Installation Instructions

Note: Regardless of the handle / modem / cable configuration you ordered, these assembly instructions are provided as a reference.

Installing the Power Cable

Step 1: Connect the power supply to the charger by aligning the connector on the power supply to the power connector on the bottom of the charger and firmly press them together (Figure 2). Power supply ordering options are as shown in Figure 3 left.

Step 2: Thread the power cable on the side of the charger and out the end as shown (Figure 4). The power cable is now installed.



Figure 2



Figure 4

Installing the Modem

Step 1: The charger is shipped with four screws for attaching a CodeXML modem to the charger. Turn the charger over.

Step 2: Place the CodeXML Modem into the charger with the 8-pin DIN connector facing away from battery charging connectors.

Step 3: Secure the modem with the four screws provided (Figure 5).

Step 4: Attach the cable to the modem by aligning the 8-pin DIN connectors and firmly pushing them together (Figure 6). Cables can be ordered with USB, RS232 or PS2 interfaces (Figure 7 left).

Step 5: Thread the cable through the opening at the end of the charger that is aligned with the 8-pin DIN connector. The modem is now assembled to the charger.



Figure 5



Figure 6

BH1/BH2 Charger Mounting Instructions

Note: When mounting charger to the wall, first install the retainer clip with washer and screw (Step 1). Retainer clip prevents handle from falling out of charger. If mounting to countertop - start at Step 2 and do not install retainer clip.

Step 1: When mounting the charger to the wall (only), slide the retainer clip into the slot from the back of the charger (Figure 8). Secure with washer and screw from the back (Figure 9).

Step 2: Secure the charger to the wall or countertop with appropriate sized screws (see note left) with consideration for anchor-mount screws as needed.

Step 3: Rest top of handle in top slot and gently slide bottom of handle onto charging pins (Figure 10).



Figure 8



Figure 9



Figure 10